


B1 Electronics box and B1 two-gang junction box



B1 Two-gang junction box

- 6 screw domes
- Suitable for all types of formwork
- 2-part with moulded-on rear part
- Two slots for connection of B¹ Prefix® system wing brackets
- rear part of box with holder for support element
- Standardised combination distance 71 mm

Order number:	1269-01
EAN:	4013456550537
Length	160 mm
Width	75 mm
Depth	91 mm
Installation opening Ø	60 x 131 mm
Break-out openings for DIN EN Ø 20/25 mm conduits	7
Break-out openings for DIN EN Ø 32/40 mm conduits	2
Markings for cables up to Ø 16 mm	7
Number of parts	9
Packaging inner/dispatch	5/50

The B1 electronics box and B1 two-gang junction box are especially suitable for installations in on-site mixed concrete vertical formwork. The electronics box provides plenty of space for accessory installations, and additional space for devices such as switch actuators or other components for smart home applications. The relevant separator wall allows the standardised installation of bus and operating voltages in a single box. Two-gang junction boxes allow the installation of block and pre-wired accessories, and provide space for the assembly of cable for multimedia connections.

- Plenty of space for accessories and cables
- Separator wall for the standardised incorporation of two voltage types
- Flat front part for fast, easy nailing
- Innovative conduit entries for fast fitting on the building site
- Slot for B¹ Prefix® system wing set
- Spring travel ensures secure fit in standing formwork

