

## Vimar - 20135.1 - Universal MASTER dimmer 230V grey

<b>Code</b>	20135.1
<b>Family</b>	Eikon / Devices / Electronic devices
<b>Description</b>	Universal MASTER dimmer 230V grey
<b>Long Description</b>	Universal-dimmer 230 V~ 50 Hz, phase-cutting, for: 40-400 W incandescent lamps, 40-300 VA electronic transformers, 10-200 W CFL lamps, 3-200 W LED lamps and LED phase-cutting electronic transformers, ON/OFF control and built-in or from NO peripheral push buttons regulation, MASTER function for 20137, minimum brightness regulation, visible in darkness, grey. Not for Isoaset enclosures
<b>Product Status</b>	3 - Active
<b>Minimum order quantity</b>	10 NR



### Sheets, Manuals

[FI - Instructions sheet \(2520 kb\)](#)

### Certifications

- 31. TISI - Thailand
- 99. WEEE Directive ([download](#))

### Technical data

**Class group:** Domestic switching devices

**Class:** Dimmer

**Method of operation:** Push button

**Type of load:** Universal and LED Retrofit

**Applicable with button:** Yes

**Applicable with movement senso:** No

**Applicable with presence indic:** No

**Applicable with time switch/ti:** No

**Applicable with transmission b:** No

**Applicable with infrared butto:** No

**Mounting method:** Flush mounted (plaster)

**Type of fastening:** Snapper mounting

**Material:** Plastic

**Surface protection:** Untreated

**Colour:** Grey

**RAL-number (akin):** 7.024,00

**Transparent:** No

**Suitable for degree of protect:** IP40

**Nominal power:** 40,00 - 400,00 VA

**Nominal voltage:** 230,00 v

**Frequency:** 50,00 HZ

**Control voltage:** 230,00 v

**Width of device:** 22,30 mm

**Height of device:** 49,00 mm

**Depth of device:** 50,70 mm

## Packaging

---

**8 007352 555853**

**Code** 8007352555853  
**Quantity** 1 NR  
**Dim.** 5.1x4.3x5.3 [cm]  
**Weight** 54.8 [g]

**8 007352 555860**

**Code** 8007352555860  
**Quantity** 10 NR  
**Dim.** 26.9x11.6x4.9 [cm]  
**Weight** 613 [g]

## Share

---



## Legal

---

Vimar reserves the right to change at any time and without notice the characteristics of the products reported.  
Installation should be carried out by qualified staff in compliance with the current regulations regarding the installation of electrical equipment in the country where the products are installed.  
For the terms of use of the information on the product info sheet see [conditions of use](#).